



## MMATS Monster 10 dual 2 or 4 ohm

Theil/Small	Dual 4 ohm	Dual 2 ohm
Znom=	N/A	1.000 ê
Sd=	N/A	0.0305 sqM
Fi=	N/A	33.102 Hz
Revc=	N/A	1.000 ê
Fo=	N/A	33.337 Hz
Krm=	N/A	0.057 mê
Vas=	N/A	14.0010 Litr
Qms=	N/A	2.768
Xmx=	N/A	11.0000 mM
Kxm=	N/A	53.900 mH
Cms=	N/A	105.9891 uM/N
Qes=	N/A	0.430
Cmx=	N/A	11.0000 mM
Erm=	N/A	1.104
Mms=	N/A	215.0480 Gram
Qts=	N/A	0.372
Exm=	N/A	0.538
Mmd=	N/A	211.9852 Gram
Pmx=	N/A	800.000 Wrms
SPLo	N/A	82.70 db



Model	Sealed (Net)	Vented (Net)	Port Specs	Port Disp	Woofer Disp
Monster 10	<u>N/A</u>	1.50 cu.ft	15 sq." X 18" Long	.10 cu.ft	.12 cu.ft.

Hole Cutout Diameter	9.125"
Overall Diameter	10.5"
Mounting Depth	5.875"

**\*\* Enclosure Size is NET Interior Volume, EXCLUDING speaker and port displacement!!**

**3" round port equals 7.07 sq. inches**

**4" round port equals 12.56 sq. inches**

**6" round port equals 28.26 sq. inches**

